

CAM SWITCHES

▶ 1 SPEED STARTER, FORWARD/OFF/REVERSE - 3 PHASE MOTOR



 Technical Info (p. 224)

IN ENCLOSURE

IP40 standard - IP65 available upon request

Contact Configuration - 9153

| No. of contacts | REV | | | FWD | |
|-----------------|-----|---|---|-----|---|
| | Δ | Y | 0 | Y | Δ |
| 1 - 2 | | | | X | X |
| 3 - 4 | X | X | | | |
| 5 - 6 | X | X | | | |
| 7 - 8 | | | | X | X |
| 9 - 10 | X | | | | X |
| 11 - 12 | X | | | | X |
| 13 - 14 | | X | | X | |
| 15 - 16 | | X | | X | |
| 17 - 18 | X | | | | X |
| 19 - 20 | X | X | | X | X |



NZ13GXQ






SZ13GXQ



TZ13GXQ

Mounting and Dimensions see pg 226 to 229

| Switch Series | General use rating - amps | Number of contacts | Positions | Designation | Part Number |
|---------------|---------------------------|--------------------|---|-------------------|-------------|
| PR12 | 12 | 10 |  | PR12 9153 C8 BCQ3 | NZ13GXQ |
| PR17 | 16 | 10 |  | PR17 9153 C8 BCQ3 | SZ13GXQ |
| PR21 | 20 | 10 |  | PR21 9153 C8 BCQ3 | TZ13GXQ |