

# MS2302

## DIGITAL EARTH TESTER

- Measuring earth resistance by constant current inverter 800Hz approx. 3mA, earth voltage by rectifier type 5k  $\Omega$  /V approx. 40~500Hz
- Two-pole and three-pole test mode
- **Data logging**, Max /Min /Avg value and relative measurement
- Large LCD display with analog bar graph & backlit

### Technical specifications

Earth resistance: 10  $\Omega$ ,  $\pm 1.0\%$ ;

100/1k/4k  $\Omega$ ,  $\pm 3.0\%$

Earth voltage: 1.0V~50.0V (50/60Hz),  $\pm 1.0\%$

Dimensions: 180x140x65mm

Battery: 1.5Vx6, AA size

Weight: approx. 900g

