



PM8908C

AC VOLTAGE DETECTOR WITH TORCH LAMP

- Non-contact detection of AC voltage with sound /light indication
- Different sound /light indication for 3 AC voltage levels (high /medium /low)
- Neutral /Live wire detection
- Built-in torch lamp
- Low battery indication, auto power off
- Safety as per IEC1010-1 Cat.III 1000V
- Ideal for electrical engineers and homeowners

Technical specifications

Voltage range: AC 12V~1000V

Frequency: 50~60Hz

Alarm: buzzer and LED bar-graph

NCV level: high /medium /low (3 levels)

Dimensions: 156x20x20mm

Battery: 1.5Vx2, AAA size

Weight: approx. 45g

PEAKMETER®

by Sinometer

www.peak-meter.cn

Email: sales@peak-meter.cn